

Phoenix Smart IP43 Charger 120-240V

Natural convection cooled

Bluetooth enabled

www.victronenergy.com



Phoenix Smart 12/50(1+1)



Bluetooth sensing:
Smart Battery Sense



Bluetooth sensing:
BMV-712 Smart Battery Monitor



Phoenix Smart 12/50(3)

Bluetooth Smart built-in

The wireless solution to set-up, monitor, update and synchronise Phoenix Smart IP43 Chargers.

Phoenix Smart (1+1): two outputs to charge 2 battery banks

The second output, limited to approximately 4A and with a slightly lower output voltage, is intended to top up a starter battery.

Phoenix Smart (3): three full current outputs to charge 3 battery banks

Each output can supply the full rated output current. But the total of the 3 outputs combined can never exceed the current rating of the charger.

Automatic voltage compensation

The charger compensates for voltage drop over the DC cabling by slightly increasing output voltage when the DC current increases. Please see the manual for details.

Adaptive 6-stage charge algorithm: bulk – absorption – recondition – float – storage – refresh

The Phoenix Smart Charger features our well-known 'adaptive' battery management system that can be preset to suit different types of batteries. The 'adaptive' feature will automatically optimise the charge process relative to the way the battery is being used.

The right amount of charge: variable absorption time

When only shallow discharges occur (a yacht connected to shore power for example) the absorption time is kept short in order to prevent overcharging of the battery. After a deep discharge the absorption time is automatically increased to make sure that the battery will be fully charged.

Preventing damage due to excessive gassing: the BatterySafe mode (see fig. 2)

If, in order to quickly charge a battery, a high charge current in combination with a high absorption voltage has been chosen, the charger will prevent damage due to excessive gassing by automatically limiting the rate of voltage increase once the gassing voltage has been reached (see the charge curve between 14,4 V and 15,0 V in fig. 2).

Less maintenance and aging when the battery is not in use: the Storage Mode (see fig. 1 & 2)

The Storage Mode kicks in whenever the battery has not been subjected to discharge during 24 hours. In the Storage Mode float voltage is reduced to 2,2 V/cell (13,2 V for a 12 V battery) to minimize gassing and corrosion of the positive plates. Once a week the voltage is raised back to the absorption level to 'equalize' the battery. This feature prevents stratification of the electrolyte and sulphation, a major cause of early battery failure.

Also charges Li-ion (LiFePO₄) batteries

Charger on-off control can be implemented by connecting a relay or open collector optocoupler output from a Li-ion BMS to the remote on-off port. Alternatively full control of voltage and current can be achieved with Bluetooth.

Fully programmable charge algorithm

The charge algorithm can be programmed with help of Bluetooth or the VE.Direct interface. Three preprogrammed algorithms can be selected with the mode button (see specifications).

Optional external battery voltage and temperature sensing via Bluetooth

A Smart Battery Sense or a BMV-712 Smart Battery Monitor can be used to communicate battery voltage and temperature to one or more Phoenix Smart IP43 Chargers.

Remote on-off

The remote on/off consists of two terminals: Remote H and Remote L. A remote on/off switch or relay contact can be connected between H and L. Alternatively, terminal H can be pulled high, or terminal L can be pulled low. See manual for details.

VE.Direct interface

For a wired data connection to a Color Control panel, PC or other devices. Please see the VictronConnect app under Downloads / Software on our website.

Programmable relay


Can be programmed using the VE.Direct interface or a Bluetooth enabled device to trip on an alarm or other events.

Synchronized charging

Pairing two or more Phoenix Smart IP43 Chargers in a VE.Smart Network, enables synchronised charging. This improves the charge efficiency and battery life.

Learn more about batteries and battery charging

For more information about adaptive charging please look under Downloads / White papers on our website.



| Phoenix Smart IP43 Charger | 12/30 (1+1) & (3) | 12/50 (1+1) & (3) | 24/16 (1+1) & (3) | 24/25 (1+1) & (3) |
|---|--|----------------------|---|----------------------|
| Input voltage | 85 - 250VAC (full power from 100VAC, startup from 90VAC) | | | |
| DC input voltage range | 90 – 375 VDC | | | |
| Frequency | 45-65 Hz | | | |
| Power factor | 1 | | | |
| Back current drain | <1mA | | | |
| No load power consumption | 1 W | | | |
| Maximum Efficiency | 95% | 94% | 96% | 96% |
| Charge voltage - Absorption / Float / Storage | Normal: 14.4V / 13.8V / 13.2V High: 14.7V / 13.8V / 13.2V Li-ion: 14.2V / N/A / 13.5V | | Normal: 28.8V / 27.6V / 26.4V High: 29.4V / 27.6V / 26.4V Li-ion: 28.4V / N/A / 27.0V | |
| Fully programmable | Yes, with Bluetooth and/or VE.Direct | | | |
| Maximum input current setting | 3 – 10A | | | |
| Number of battery connections | (1+1) models: 2 (2nd output via 2 pole terminal & 4A max) (3) models: 3 | | | |
| Charge current house battery | 30 A | 50 A | 16 A | 25 A |
| Low current mode | 15 A | 25 A | 8 A | 12,5 A |
| Temperature compensation - Default | -16mV/°C | | -32mV/°C | |
| Charge current starter battery | 4 A Max (1+1 output models only) | | | |
| Charge algorithm | 6-stage adaptive (3 stage for Li-ion) | | | |
| Protection | Battery reverse polarity (fuse, not user accessible) / Output short circuit / Over temperature | | | |
| Can be used as power supply | Yes, output voltage can be set with Bluetooth and/or VE.Direct | | | |
| Operating temp. range | -20 to 60°C (0 - 140°F) Rated output current up to 40°C, derate linearly to 20% at 60°C | | | |
| Humidity (non-condensing) | max 95% | | | |
| Remote on/off | Yes (2 pole terminal) | | | |
| Relay (programmable) | Yes (SPDT - 5A up to 250VAC / 5A up to 28VDC) | | | |
| Bluetooth | Power: -4dBm Frequency: 2402 - 2480MHz | | | |

ENCLOSURE

| | |
|------------------------|---|
| Material & Color | aluminium (blue RAL 5012) |
| Battery connection | Screw terminals 16 mm ² (AWG6) |
| AC-connection | IEC 320 C14 inlet with retainer clip (AC cord ordered separately) |
| Protection category | Electronic components: IP43 Connection area: IP22 |
| Weight kg (lbs) | 2,7 kg (6 lbs) |
| Dimensions (h x w x d) | 180 x 249 x 116 mm (7.1 x 9.8 x 4.6 inch) |

STANDARDS

| | |
|-----------|--|
| Safety | EN 60335-1, EN 60335-2-29 |
| Emission | EN 55014-1, EN 61000-6-3, EN 61000-3-2 |
| Immunity | EN 55014-2, EN 61000-6-1, EN 61000-6-2, EN 61000-3-3 |
| Vibration | IEC68-2-6:10-150Hz/1.0G |



Retainer clip
(included)



Mains Cord CEE 7/7
(must be ordered separately)



Mains Cord NEMA 5-15P plug
(must be ordered separately)

Plug options:

Europe: CEE 7/7
UK: BS 1363
Australia/New Zealand: AS/NZS 3112
US: NEMA 5-15P

Charge curves: up to the gassing voltage (fig.1), and exceeding the gassing voltage (fig.2)

